

# ECLIPSEFS

## DMX CONTROL

								FUNCTION	DMX Value
1CH	3CH	3CH RGB	4CH RGLB	5CH	5CH RGLB	8CH	13CH		
1	1			1	1	1	1	<b>Dimmer</b> Dimmer(Close to Open)	000 - 255
				2			2	<b>Dimmer fine</b> Dimmer fine 0->100%	000 - 255
	2			3				<b>CTC</b> CTC 2000K ->10000K	000 - 255
				4				<b>CTC Fine</b> CTC Fine	
		1	1		2	2	3	<b>Red</b> Red 0->100%	000 - 255
							4	<b>Red fine</b> Red fine 0->100%	000 - 255
		2	2		3	3	5	<b>Green</b> Green 0->100%	000 - 255
							6	<b>Green fine</b> Green Fine 0->100%	000 - 255
		3	3		4	4	7	<b>Blue</b> Blue 0->100%	000 - 255
							8	<b>Blue fine</b> Blue Fine 0->100%	000 - 255
			4		5	5	9	<b>Lime</b> Lime 0->100%	000 - 255
							10	<b>Lime fine</b> Lime Fine 0->100%	000 - 255
						6	11	<b>Virtual Color</b> No Function Red Green Blue Lime Cyan Magenta Yellow Orange Light Yellow Light Blue Light Pink 2000K->2700K 2700K->3200K 3200K->4200K 4200K->5600K 5600K->8000K 8000K->10000K	000 - 003 004 - 005 006 - 007 008 - 009 010 - 011 012 - 013 014 - 015 016 - 017 018 - 019 020 - 021 022 - 023 024 - 025 026 - 063 064 - 101 102 - 139 140 - 177 178 - 215 216 - 255
						7	12	<b>Shutter Function</b> Normal Shutter Functions Strobe effect slow to fast	000 - 003 003 - 255
	3			5		8	13	<b>Dimmer Fade</b> 0->100%	000 - 255